
# Function:

The 620e Bronze Series Sand Filter System is our most economical underground vault sand filter system available. Made using schedule 40 PVC piping, ball valves, and fittings, it features high quality components and reliable construction all housed in a water tight, fiberglass vault with aluminum access hatch. This system can only be housed in a 6PAK vault. (as shown)



### 620e Pumping Options -

- Hobbs 315-44: 1/2 through 3 HP Series Centrifugal Pump. 1 or 3 phase power or
- Hobbs 320-HP: 5 HP Centrifugal Pump. 3 phase power
- 115/208-230/460V available. Installer must provide additional 120V line for 460V systems
- · Basket strainer included

#### 620e Filtration System -

- Hobbs 352-60D Series Tagelus Sand Filter
- 60 GPM max through filter, system includes bypass line for remainder of flow
- Fiberglass reinforced tank
- · Six position, clamp style, top mounted multiport valve

#### **Chemical Treatment (Optional) -**

- Hobbs 360e-BS Brominator Assembly
- 25,000 gallon capacity
- 60 GPM max through brominator, system includes bypass line for remainder of flow
- Standard system includes selected PAK size, selected pump size, cartridge filter. Sump pump is standard with 6PAK, optional with 4PAK.
- Bulkhead fittings are placed at suction and discharge points on PAK walls for installer piping to fountain.
- Control panel requirements vary depending on pump selection. A control panel is required for all systems.

Model	Order#	Description	Suct.	Disch.
620e-005-1-B	680-69730	Bronze Series, 1/2 HP, 1φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-005-3-B	680-69732	Bronze Series, 1/2 HP, 3φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-007-1-B	680-69734	Bronze Series, 3/4 HP, 1φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-007-3-B	680-69736	Bronze Series, 3/4 HP, 3φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-010-1-B	680-69738	Bronze Series, 1 HP, 1φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-010-3-B	680-69740	Bronze Series, 1 HP, 3φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-015-1-B	680-69742	Bronze Series, 1 1/2 HP, 1φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-015-3-B	680-69744	Bronze Series, 1 1/2 HP, 3φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-020-1-B	680-69746	Bronze Series, 2 HP, 1φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-020-3-B	680-69748	Bronze Series, 2 HP, 3φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-030-1-B	680-69750	Bronze Series, 3 HP, 1φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-030-3-B	680-69752	Bronze Series, 3 HP, 3φ, Sand Filter System for ePAK	One 2"	Two 2"
620e-051-3-B	680-69754	Bronze Series, 5 HP, 3φ, Sand Filter System for ePAK	One 3"	Two 3"
Optional Equipment				
360e-BS	680-69619	Brominator Assembly	N/A	N/A
600-1304	610-61111	Sump Pump Assembly (Standard with 6PAKs)	N/A	N/A

## 620e Bronze Series



#### **PUMP INFORMATION:**

1/2 HP; 1 Phase; 115/208-230V; Delivers 76 GPM at 30 feet of head, 55 GPM at 50 feet of head, 16 GPM at 70 feet of head.

1/2 HP; 3 Phase; 208-230/460V; Delivers 77 GPM at 30 feet of head, 55 GPM at 50 feet of head, and 37 feet of head at 70 GPM.

3/4 HP; 1 Phase; 115/208-230V; Delivers 88 GPM at 30 feet of head, 71 GPM at 50 feet of head, and 47 GPM at 70 feet of head.

**3/4 HP; 3 Phase;** 208-230/460V; Delivers 88 GPM at 30 feet of head, 70 GPM at 50 feet of head, and GPM at 70 feet of head.

1 HP; 1 Phase; 115/208-230 V; Delivers 100 GPM at 40 feet of head, 76 GPM at 60 feet of head, and 42 GPM at 80 feet of head.

1 HP; 3 Phase; 208-230/460V; Delivers 110 GPM at 30 feet of head, 90 GPM at 50 feet of head, and 63 GPM at 70 feet of head.

1-1/2 HP; 1 Phase; 208-230V; Delivers 110 GPM at 50 feet of head, 85 GPM at 70 feet of head, and 66 GPM at 80 feet of head.

**1-1/2 HP; 3 Phase;** 208-230/460V; Delivers 130 GPM at 30 feet of head, 110 GPM at 50 feet of head, and 85 GPM at 70 feet of head.

2 HP; 1 Phase; 208-230V; Delivers 125 GPM at 50 feet of head, 97 GPM at 70 feet of head, and 78 GPM at 80 feet of head.

2 HP; 3 Phase; 208-230/460V; Delivers 150 GPM at 30 feet of head, 125 GPM at 50 feet of head, and 98 GPM at 70 feet of head.

3 HP; 1 Phase; 208-230V; Delivers 141 GPM at 60 feet of head, 110 GPM at 80 feet of head, and 50 GPM at 100 feet of head.

3 HP; 3 Phase; 208-230/460V; Delivers 160 GPM at 50 feet of head, 130 GPM at 70 feet of head, and 90 GPM at 90 feet of head.

**5 HP; 3 Phase**; 208-230/460V; Delivers 195 GPM at 60 feet of head, 155 GPM at 80 feet of head, 100 GPM at 95 feet of head.

Toll Free: 887.426.4622 Phone: 770.457.3000 Fax: 770.457.4225 www.hobbsfountains.com